

## SIRIUS ENERGY STORAGE MODULE TECHNICAL DATA SHEET

Part Number: 1000-48-B-1C-TM-A-G Version Date: January 2020



	Voltage (Nominal)	48 V <sub>dc</sub>
	Maximum Charge Voltage	54 V <sub>dc</sub>
PERFORMANCE	Discharge Cut-Off Voltage 44 V <sub>dc</sub>	
SPECIFICATIONS	Total Energy	1000 Wh
	Maximum Charge Rate	20 A
	Maximum Discharge Rate	20 A
ENVIRONMENTAL	Cell Operating Temperature <sup>1</sup>	-30 °C to 80 °C
SPECIFICATIONS	Operating Humidity	Non-Condensing
	Dimensions (w × d × h)	128× 1420× 118 mm
MECHANICAL	Weight	23 Kg Approx.
SPECIFICATIONS	Module Casing Material	GI
	Terminal Type	F12
SMART FEATURES	Alarm	Audible alarm in the event of Over/under- Voltage, Over-Current, Over Temperature
MODULE SERVICE LIFE	Projected Cycle Life <sup>2,3</sup>	1 million cycles
	Projected Calendar Life <sup>3,4</sup>	45 years
	Shelf Life⁵	10 years
	Warehousing	Can be stored at any SOC without affecting cycle life
COMPLIANCE <sup>6</sup> INFORMATION	EN55032:2015, EN55024:2010, EN61000-4-2:2009, EN61000 EN61000:2008+A2:2010	

This technical data sheet may change without notice and at the sole discretion of Kilowatt Labs, Inc. Solutions for: Microgrids | C&I and Residential Solar | Electric Vehicles | Utility Grade Storage Kilowatt Labs, Inc. | www.kilowattlabs.com



## SIRIUS ENERGY STORAGE MODULE TECHNICAL DATA SHEET

Part Number: 1000-48-B-1C-TM-A-G Version Date: January 2020

PRECAUTIONS	Alarm	In case of alarm, immediately rectify/attend to the cause of the alarm.	
	Physical Damage	In case the Module is physically damaged due to any event, do not install and energize the Module under any circumstances and contact your Reseller.	
	Short Circuit	Ensure precautions to prevent short-circuit under all circumstances.	
	Galvanic isolation	When connecting to external devices ensure that galvanic isolation does not exceed 1000V.	
	Charge/Discharge Current	Under no circumstances must the charge/discharge current exceed 20A.	
	Charging Voltage	Under no circumstances must the charging voltage exceed 54 $V_{dc}$ for more than 60 seconds.	
	Charge Cycle	During charge cycle ensure never to exceed constant voltage of $54 V_{dc}$ and constant current of 20A.	
	Series Connection	<ul> <li>All Modules must be at 100% SOC before connecting in series.</li> <li>A maximum of 8 Modules can be connected in series.</li> <li>Please consult your Reseller when connecting the Modules in series. Under no circumstances should more than 8 Modules be connected.</li> </ul>	
	Parallel	There is no limit on the number of Modules that can be	
	Connection	connected in parallel.	
	Series-Parallel	Modules cannot be connected in Series-Parallel combination	
	Connection	under any circumstance.	
		hich the supercapacitor cells can operate. The performance of the cells may vary perature range of $-10^{\circ}$ C to $55^{\circ}$ C and/or at C-rates higher than the maximum	

<sup>1</sup>The temperature range indicates the range in which the supercapacitor cells can operate. The performance of the cells may vary if they are continuously operated outside a temperature range of -10°C to 55°C, and/or at C-rates higher than the maximum charge/discharge rate specified in this spec sheet. The operating temperature range of the Module varies based on the application. If the Module is to be operated continuously outside a temperature range of -10°C to 55°C, and/or at C-rates higher than the maximum charge/discharge rate specified in the spec sheet, please consult Kilowatt Labs or its Reseller prior to deploying. <sup>2</sup>Projected life of supercapacitor cells. Cycle life will vary if cycled more than 4 times a day.

<sup>3</sup>Additional terms and conditions, including a limited warranty, will apply at the time of purchase.

<sup>4</sup>Projected Calendar life of supercapacitor cells from the date of first operation.

<sup>5</sup>Shelf life is the life of the Module (in years) from the date it is manufactured to the time it is first operated.

<sup>6</sup>CE certification is completed for supercapacitor cells.

Product dimensions are for reference only unless otherwise identified and may change without notice.

For critical applications, please contact your Reseller.