

# Power Inverter

## Product card



### Specification:

|  |                           |
|--|---------------------------|
| <b>Input voltage [V]:</b>                                      | 24V                       |
| <b>Output Power/Peak Power:</b>                                | 500W / 1000W              |
| <b>Sine Wave:</b>  | Pure                      |
| <b>Socket type:</b>  | F                         |
| <b>Fuse Rating [A]:</b>  | 30A                       |
| <b>Number of fuses:</b>  | 2                         |
| <b>Current consumption without load [A]:</b>                   | 0,35A                     |
| <b>No-load power consumption:</b>                              | 8,4A                      |
| <b>Efficiency at a load of approx. 90% of the rated power:</b> | 85%                       |
| <b>Dimensions (LxWxH):</b>                                     | 22,0 x 10,6 x 6,0 cm      |
| <b>Dimensions with mounting bracket:</b>                       | 22,5 x 10,6 x 6,2cm       |
| <b>Weight (g):</b>   | 1090g                     |
| <b>Cross-section of cables included in the kit (mm ^ 2):</b>   | 6                         |
| <b>Number of wire pairs included in the kit:</b>               | 1 + 1 with car plug 12VDC |